



BOSCH
Invented for life

LBB 1995/00 Plena Voice Alarm System Fireman's panel

- ▶ Remote Control of the Voice Alarm System
- ▶ Emergency (EMG) microphone
- ▶ EMG and background (BGM) zone selections
- ▶ EMG state and fault indicators
- ▶ Control outputs for EMG and Fault state Front panel zone selection for BGM and call station zone selection for calls

The Plena Voice Alarm Remote Control panels offer operational control at up to two remote locations. The main RC unit offers the front panel of the voice alarm controller, while the RC extensions offer the control of the routers. Both remote controls (LBB 1996 & LBB 1997) are available as a kit to manufacture tailor made solutions. Also available is a fireman's panel that features large illuminated buttons and an all call functionality.

Functions

The remote control is an exact match to the voice alarm controller with all controls and indicators at the same location. The remote control has BGM zone selection but not source selection, volume and tone controls. The remote control extension is a match to the router. The volume units (VU) meter shows the presence and level of the calls that are running in the system. The fault indicators show detailed information of a fault in the system. Connection to the Bosch Voice Alarm System is done via standard shielded CAT 5 cable and RJ45 connectors. Included in the delivery are rack mount brackets that can also be used to mount the units to a rear wall with spacing for cables and even to a flat surface above or below the units.

The kits LBB 1998 & LBB 1999 are a functional match to the remote control and the RC extension, with connectors on the front panel instead of controls and indicators. With these kits it is possible to reliably build a custom control unit with confidence and ease. The electrical connections are printed on front and rear panels. A 24 VDC output is available to supply power to external LEDs and relays, so no external power supply is required for that purpose. An LED VU-meter allows for monitoring of the master output.

The fire panel, remote control and remote control kit function on an external 24V power supply. The RC extension and extension kit are powered by the interconnecting CAT-5 (shielded) cable.

Certifications and Approvals

EMC emission
EMC immunity

Acc. to EN 55103-1
Acc. to EN 55103-2

Parts Included

Quantity	Component
1	LBB 1995/00 – LBB 1999/00
1	EMG microphone and cable (except extension)
1	1 m CAT-5 cable
2	19" mounting brackets
1	EMG mic mounting clip
1	Release notes
1	Plena CD with configuration software, installation and user instructions, audio tools, free music and more

Technical Specifications

Electrical

24 V input	24 VDC, +20% / -10%
battery current	Typical – max (indicator test)
LBB 1995/00	100 mA – 250 mA
LBB 1996/00	100 mA – 250 mA
LBB 1997/00	50 mA – 200 mA
LBB 1998/00	100 mA – 250 mA
LBB 1999/00	50 mA – 200 mA

Performance*

Relays

Priority relay contacts	30 V, 1 A
Emergency relay contacts	30 V, 1 A
DC supply output voltage	24 V, 200 mA max

LEDs / LAMPs

(KITS)	
LEDs on internal power	5 mA max
External power	50V – 200 mA max
Type	Open collector pull down

Environmental

Operating temperature range	-10°C to +55°C
Storage temperature range	-40°C to +70°C
Relative humidity	<95%

General

Dimensions

LBB 1995/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1996/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1997/00	88 x 430 x 90 mm (19" wide, 2U high)
LBB 1998/00	134 x 430 x 90 mm (19" wide, 3U high)
LBB 1999/00	88 x 430 x 90 mm (19" wide, 2U high)

Weight approx.	3 kg
----------------	------

*) Technical performance data acc. to IEC60268-3

Ordering Information

Model | Description

LBB 1995/00 Plena Voice Alarm System Fireman's panel
All call EVAC Remote Control with microphone

Americas:
Bosch Security Systems
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 585 223 4060
Fax: +1 800 289 0096
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 (0) 40 27 83955
Fax: +31 (0) 40 27 86668
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by